

# M-04044K / M-08084K

4x4, 8x8 HDMI 4K Matrix Switcher M Series



The 4x4 and 8x8 HDMI Matrix with EDID control connects for 4/8 HDMI sources to 4/8 displays. This matrix provide 4/8 HDMI outputs and each HDMI output is supporting 1080p Full HD up to 4K plus all 3D formats and supporting independent EDID control. It works with Blu-Ray players, Set-Top boxes, Home Theater PCs, and game consoles that connect to an HDMI display. Any source is accessible at all times by any display by selecting it via the supplied IR Remote Control, RS-232, TCP/IP or by using the selection buttons on the Front Panel.

## **FEATURES**


#### M-04044K


- Input: 4 x HDMI, 4 x IR
- Output: 4 HDMI, 4 x IR
- Resolution:480i,576i,480p,576p,720p,1080i, 1080p@24/30/50/60Hz, 4K@30Hz, 1080P3D@60Hz
- Dimensions: 440 mm (W)×200 mm (D)×45 mm (H)
- Operating Temperature: 0 ºC~40 ºC
- Relative Humidity: 20~90 % RH (non- condensing)
- Power Consumption: 23W(Max)/0.5W(Standby)
- Power adaptor: 100-240VAC

### M-08084K

- Input: 8 x HDMI, 8 x IR
- Output: 8 HDMI, 8 x IR, Coaxial Audio x 8
- Resolution:480i,576i,480p,576p,720p,1080i,
- 1080p@24/30/50/60Hz, 4K@30Hz,
- 1080P3D@60Hz
- Dimensions: 440 mm (W)×200 mm (D)×45 mm (H)
- Operating Temperature: 0 ºC~40 ºC
- Relative Humidity: 20~90 % RH (non- condensing)
- Power Consumption: 23W(Max)/0.5W(Standby)
- Power adaptor: 100-240VAC

# **TECHNICAL SPECIFICATIONS**





- 1 LCM
- 2 IR receiver window
- 3 POWER
- 4 LOCK
- 6 HDMI output selection button area.
- 6 HDMI input selection button area.
- PTP button



- 1 PC Control (TCP/IP and RS232)
- 2 Power Port
- 3 IR EXT
- 4 IR Receiver
- IR TransmitterCoaxial Audio Output
- HDMI Input Area
- 8 HDMI Output Area



#### **About VitBes**

VitBest is a professional digital audio video products manufacturer dedicates in manufacturing high quality, reliable and stable products. For audio-visual system integrators, a trustworthy distribution and control electronics components means much more than their sizes.